

Total No. of printed pages = 4

EI 181405

Roll No. of candidate

--	--	--	--	--	--	--	--	--	--

2023

B.Tech. 4th Semester End-Term Examination

SIGNALS AND SYSTEMS

New Regulation

(w.e.f. 2017-18) & New Syllabus (w.e.f. 2018-19)

Full Marks – 70

Time – Three hours

The figures in the margin indicate full marks for the questions.

Answer Question No. 1 and any *four* from the rest.

1. Choose the correct answers from the following multiple choice questions :
(10 × 1 = 10)
- (i) The unit impulse is a signal with
- (a) infinite magnitude and zero duration
 - (b) infinite magnitude and zero duration but with unit area
 - (c) finite magnitude and zero duration but with unit area
 - (d) finite magnitude and infinite duration
- (ii) The signal $x(t) = \cos(2500t)$ is a
- (a) periodic and even signal
 - (b) aperiodic and even signal
 - (c) periodic and odd signal
 - (d) aperiodic and odd signal
- (iii) The response of an LTI system is called the impulse response if the input signal is
- (a) a unit step signal
 - (b) a unit ramp signal
 - (c) a unit parabolic signal
 - (d) a unit impulse signal

[Turn over

- (iv) The system characterized by the equation $y(t) = ax(t) + b$ is
- (a) linear for any value of b (b) linear for $b > 0$
 (c) linear for $b < 0$ (d) non-linear
- (v) The only non-zero Fourier series coefficient(s) of the signal $x(t) = \cos \omega t$ is/are
- (a) 1 (b) $\frac{1}{2}$
 (c) $\frac{1}{2}$ and $\frac{1}{2}$ (d) 1 and 1
- (vi) If the Fourier series coefficients of a signal are periodic, then the signal must be
- (a) continuous-time, periodic
 (b) continuous-time, non-periodic
 (c) discrete-time, periodic
 (d) discrete-time, non-periodic
- (vii) If the notation $*$ is used to denote the convolution, $X(\omega)$ and $Y(\omega)$ are the Fourier transform of $x(t)$ and $y(t)$ respectively then the Fourier transform of $x(t) * y(t)$ is
- (a) $X(\omega)Y(\omega)$ (b) $X(\omega) * Y(\omega)$
 (c) $\frac{1}{2\pi} X(\omega) Y(\omega)$ (d) $\frac{1}{2\pi} [X(\omega) * Y(\omega)]$
- (viii) The discrete time Fourier transform is periodic with period
- (a) π (b) 2π
 (c) $\pi/2$ (d) $\pi/4$
- (ix) The z- transform and ROC of a signal $x(n) = u(n)$ is
- (a) $X(z) = 1$ and ROC, $|z| = 0$
 (b) $X(z) = z$ and ROC, $|z| > 1$
 (c) $X(z) = z/(z-1)$ and ROC, $|z| > 1$
 (d) $X(z) = z/(z-1)$ and ROC, $|z| < 1$

- (x) The Nyquist rate of the signal $x(t) = \sin(200\pi t)$
- (a) 400 Hz (b) 200 Hz
- (c) 100 Hz (d) 1/200 Hz

2. (a) Plot the following signals :

(i) $x(t) = u(t+1) - u(t-1)$

(ii) $g[n] = \sum_{m=-1}^{m=1} \delta[n-2m]$ 6

(b) Determine energy and power of the signal: 5

$$x(t) = e^{-3t} u(t)$$

(c) What is meant by impulse response of an LTI system? The impulse response of an LTI system is $h[n] = e^{-4n} u[n-1]$. Is the system causal? Justify your answer. 4

3. (a) Compute the convolution of the following two signals: 5

$$x[n] = \{0, 1, -1\} \text{ and } h[n] = \{0, 1\}$$

(b) Examine the stability of a continuous-time LTI system whose impulse response is $h(t) = e^{-2t} u(t-1)$. 5

(c) Show that an LTI system with impulse response $h_1[n] = \delta[n-1]$ is the inverse of another LTI system with impulse response $h_2[n] = \delta[n+1]$. 5

4. (a) Determine the fundamental frequency and the Fourier series coefficients of continuous time periodic signal, $x(t) = 1 + \cos\left(\frac{2\pi}{5}t\right) + \sin\left(\frac{3\pi}{5}t\right)$. 7

(b) A continuous-time periodic signal $x(t)$ has the fundamental frequency ω_0 and Fourier series coefficient a_k . Determine the Fourier series coefficient of the following signals using properties:

(i) $x(t - t_0)$ and

(ii) $\frac{dx(t)}{dt}$ where t_0 is a time - shift.

5. (a) Determine the Fourier transform of the continuous-time signal and plot the magnitude and phase spectrum: $x(t) = e^{-2t} u(t)$. 7
- (b) The impulse response of a discrete-time LTI system is given by $h[n] = \left(\frac{1}{2}\right)^n u[n]$. Determine the output response $y[n]$ for the input $x[n] = \left(\frac{3}{4}\right)^n u[n]$ using Fourier Transform. 8
6. (a) State sampling theorem. Describe briefly the steps associated with the discrete-time processing of continuous-time signals. 6
- (b) What is meant by "aliasing"? What corrective measures will you put forward to combat the effect of aliasing? 6
- (c) Define Nyquist rate and Nyquist interval for sampling of a signal. 3
7. (a) Determine the z-transform of $x[n] = \left(\frac{1}{2}\right)^n u[n] + 2^n u[n]$ and depict the ROC and the locations of poles and zeros in the z-plane. 5
- (b) Explain at least two properties of z-transform. 4
- (c) Define FIR and IIR system. A system is described by the following system function. Derive its difference equation assuming $x[n]$ and $y[n]$ as input and output respectively. State whether the system is IIR or FIR? 6

$$H(z) = \frac{1 - 2z^{-1}}{1 - \frac{2}{3}z^{-1}}$$
